

Chrome Plated Brass Ball and Nickel Plated Brass Stem





Type overview	
Туре	DN
B325L	25
Technical data	

Functional data	Valve size [mm]	1" [25]
	Fluid	chilled or hot water, up to 60% glycol
	Fluid Temp Range (water)	0250°F [-18120°C]
	Body Pressure Rating	600 psi
	Close-off pressure Δps	200 psi
	Flow characteristic	modified linear
	Servicing	maintenance-free
	Flow Pattern	3-way Diverting

Flow Pattern 3-wa
Leakage rate 0%
Controllable flow range 75°
Cv 11

Valve body

Stem

nickel-plated brass

Seat

PTFE

Pipe connection

NPT

Ball

chrome plated brass

LRB(X)


Product features

Application

Materials

This valve is typically used in air handling units on heating or cooling coils, and fan coil unit heating or cooling coils. Some other common applications include Unit Ventilators, VAV box reheat coils and bypass loops. This valve is suitable for use as diverting or change over valve.


Flow/Mounting details







Dimensions

Туре	DN	Weight
B325L	25	1.32 lb [0.60 kg]



LRB, LRX





LF

 A
 B
 C
 D
 E
 F

 8.1" [206]
 3.1" [78]
 6.5" [165]
 5.6" [142]
 1.9" [48]
 1.9" [48]



Technical data sheet LF24-S US



Nominal voltage	AC/DC 24 V
Nominal voltage frequency	50/60 Hz
Nominal voltage range	AC 19.228.8 V / DC 21.628.8 V
Power consumption in operation	5 W
Power consumption in rest position	2.5 W
Transformer sizing	7 VA
Auxiliary switch	1 x SPDT, 3 A resistive (0.5 A inductive) @ AC 250 V, adjustable 095°
Switching capacity auxiliary switch	3 A resistive (0.5 A inductive) @ AC 250 V
Electrical Connection	(2) 18 GA appliance cables, 1 m, with 1/2" conduit connectors
Overload Protection	electronic throughout 095° rotation
Direction of motion motor	selectable with switch 0/1
Direction of motion fail-safe	reversible with cw/ccw mounting
Angle of rotation	90°
Running Time (Motor)	75 s / 90°
Running time fail-safe	<25 s @ -4122°F [-2050°C], <60 s @ -22°F [-30°C]
Noise level, motor	50 dB(A)
Noise level, fail-safe	62 dB(A)
Position indication	Mechanical
Power source UL	Class 2 Supply
Degree of protection IEC/EN	IP54
Degree of protection NEMA/UL	NEMA 2
Enclosure	UL Enclosure Type 2
Agency Listing	cULus acc. To UL 873 and CAN/CSA C22.2 No 24-93
Quality Standard	ISO 9001
UL 2043 Compliant	Suitable for use in air plenums per Section 300.22(C) of the NEC and Section 602 of the IMC
Ambient humidity	Max. 95% RH, non-condensing
Ambient temperature	-22122°F [-3050°C]
Storage temperature	-40176°F [-4080°C]
Servicing	maintenance-free
Weight	3.4 lb [1.6 kg]
	Nominal voltage frequency Nominal voltage range Power consumption in operation Power consumption in rest position Transformer sizing Auxiliary switch Switching capacity auxiliary switch Electrical Connection Overload Protection Direction of motion motor Direction of motion fail-safe Angle of rotation Running Time (Motor) Running time fail-safe Noise level, motor Noise level, fail-safe Position indication Power source UL Degree of protection IEC/EN Degree of protection NEMA/UL Enclosure Agency Listing Quality Standard UL 2043 Compliant Ambient humidity Ambient temperature Storage temperature Servicing

Footnotes †Rated Impulse Voltage 800V, Type of action 1.AA, Control Pollution Degree 3



Electrical installation

X INSTALLATION NOTES

A Actuators with appliance cables are numbered.

 \sum Provide overload protection and disconnect as required.

Actuators may also be powered by DC 24 V.

Actuators may be connected in parallel if not mechanically linked. Power consumption and input impedance must be observed.

One built-in auxiliary switch (1x SPDT), for end position indication, interlock control, fan startup, etc.

Apply only AC line voltage or only UL-Class 2 voltage to the terminals of auxiliary switches. Mixed or combined operation of line voltage/safety extra low voltage is not allowed.

Meets cULus requirements without the need of an electrical ground connection.

Warning! Live electrical components!

During installation, testing, servicing and troubleshooting of this product, it may be necessary to work with live electrical components. Have a qualified licensed electrician or other individual who has been properly trained in handling live electrical components perform these tasks. Failure to follow all electrical safety precautions when exposed to live electrical components could result in death or serious injury.

Wiring diagrams On/Off

